

Emergency Stop Button

The emergency stop button is an optional accessory for EcoFlow PowerOcean solar storage solution, designed to achieve rapid shutdown to cut off the power supply of the entire system. When using, press the switch button to cut off the AC power, and turn the button to close the switch, so the AC power supply is restored.



High Visibility



Operate from -20°C to 50°C



Easy Installation

Model	CE4T-10R-02
Rated Operating Voltage	24~300V
Rated Frequency	50Hz/60Hz
Rated Operating Current AC-15 (Ie)	(240V) 1 A
Rated Operating Current DC-13 (Ie)	125V) 0.2 A (24V) 0.3 A
Actuator Type	Mushroom 40mm
Function	Twist release
Mechanical Durability	0.5 million
Connection Capacity	Flexible with Ferrule 1 x 0.5~1.5 mm? Flexible with Ferrule 2 x 0.5~1.5 mm? Flexible with Insulated Ferrule 1 x 0.5~1.5 mm? Flexible with Insulated Ferrule 2 x 0.5~1.5 mm? Flexible 1 x 0.5~1.5 mm? Flexible 2 x 0.5~1.5 mm? Solid 1 x 0.5~1.5 mm? Solid 2 x 0.5~1.5 mm?
Illumination	Non-illuminated
Operating Temperature	-25°C ~ +70°C
Storage Temperature	-40°C ~ +85°C
Net Weight	Approximately 0.13 kg
Dimensions	65*65*80mm